# PM862

## Fuente de alimentación, 24 VCC, 1,5 A

This efficiency cost effective power supply is ideal for use in Fire, Access control and general security applications.

Featuring a regulated 27.6 Vdc output supplying continuous full rated current to load plus additional current for charging two x 12V standby batteries.

The highly efficient switch mode design ensures low operating costs, generates less heat and with a small physical size increases the room available for additional PCBs or cables. The modular construction simplifies maintenance.




## Detalles

- Indicadores de fallo y presencia de red eléctrica
- Desconexión de la batería para evitar una descarga profunda
- Tamperswitch
- Salidas de fallo
- Fusible de red y CC
- Carcasa de acero con recubrimiento en polvo

# PM862

## Fuente de alimentación, 24 VCC, 1,5 A

## Especificaciones técnicas

### General

| | |
|---|---|
| Fuse(s) | Entrada de 230 VCA, 2 A; salida de 12/24 V, 2 A |

### Electrical

| | |
|---|---|
| Mains input | 230 VAC |
| Operating voltage | 50/60 Hz ±10% |

### Output

| | |
|---|---|
| Power output voltage | 27.6 VDC |
| Power output current mains | 2 A |

### Battery

| | |
|---|---|
| Max. Battery capacity | 7.2 Ah (x2) |
| Battery charge current | 0.5 A |
| Battery recharge time | 20 hours |
| Battery disconnect voltage | 19.6 ±0.2 VDC |

### Physical

| | |
|---|---|
| Physical dimensions | 330 x 275 x 80 mm (W x H x D) |
| Colour | Weiß |
| Form factor | Stahlschrank |

### Environmental

| | |
|---|---|
| Operating temperature | -10 to +40°C |
| Relative humidity | 95% |

### Regulatory

| | |
|---|---|
| Compliancy | CE, REACH, RoHS 2, WEEE |

### Salida de carga

| | |
|---|---|
| | 1.5 A |

### Salida de colector abierto

| | |
|---|---|
| | Circuito abierto ON |
| | fallo o fallo de la red eléctrica |
| | - 0 V - 100 mA |

### Carcasa (acero) con recubrimiento en polvo

| | |
|---|---|
| | 1.2 mm |

Como empresa innovadora, Kidde Global Solutions se reserva el derecho de modificar las especificaciones de los productos sin previo aviso. Para conocer las últimas especificaciones de los productos, visite la Web de es.firesecurityproducts.com o póngase en contacto con su comercial.

Last updated on 12 November 2026 - 18:57