SC-11-1201-0001-32

SmartCell Wireless Control Panel (No Comms Module) - French (Belgium)

SmartCell overview

SmartCell has been designed as a complete wireless fire detection system to protect people and property. The system incorporates separate information zones which allow input devices to be configured in multiple configurations, providing maximum flexibility to the user and designer.

A SmartCell system can support up to 64 wireless devices consisting of 32 fire devices and 32 information devices.

Communication between devices and the control panel is bidirectional and operates in the European harmonised 868MHz frequency band.

With significant time saving against conventional and addressable fire system installations, no cables, no mess and no inconvenience to everyday business, SmartCell is perfect for all small to medium sized fire system installations.



Détails

- Entièrement sans fil
- Rapide et facile à installer
- Boîtier compact
- Affichage OLED de 80 caractères
- Permet de recevoir une carte de communication interne pour la connexion aux services SmartCell
- Version 24 VDC également disponible

SC-11-1201-0001-32

SmartCell Wireless Control Panel (No Comms Module) - French (Belgium)

Spécifications techniques

General

User interface	16 zone indicators
Maximum system capacity (device count)	1 to 32

Electrical

Power supply type	230 VAC
Operating voltage	220 to 240 VAC, 50 Hz, 0.3 A
Current consumption	5 mA (PSU), plus 100 mA from control panel

Zone

Maximum zone capacity	up to 16

Standby battery

Capacity	6 V 4 Ah

Physical

Form factor	Compact
Physical dimensions	275 x 220 x 80 mm (W x H x D)
Net weight	1.55 kg
Mounting type	Surface mount
Cable entries	4 x 100 mm (bottom) / 4 x 100 mm (back)

Environmental

Operating temperature	-5°C to +45°C
Storage temperature	0°C to +30°C
Relative humidity	95% noncondensing max.
Environment	Indoor
IP rating	IP30

Regulatory

Compliancy	CE
Certification	CPR
Standards	EN54-2 EN54-4 EN54-13 EN54-25

En tant que société d'innovation, Kidde Global Solutions se réserve le droit de modifier les spécifications des produits sans préavis. Pour les dernières spécifications du produit, visitez le site web be.firesecurityproducts.com ou contactez votre représentant commercial.

Last updated on 12 November 2026 - 18:57